


220/240 V normal and emergency "light duty" luminaires for armoured or non-armoured cable zone 2 and 22



300239 2 x 58W



300235 2 x 18W



Charge indicating light

LIGHT DUTY VERSION

18, 36 and 58 W fluorescent luminaires for normal and emergency lighting







- Ø 26 mm mono and bi-pin tubes, standard G13 lampholders
- Frequency : 50/60 Hz
- Common power supply circuit to provide both normal lighting and emergency lighting
- Power supply via high frequency ballast 220/240 V~ (± 10%)
- Instant start - Power factor ≥ 0.95
- Battery voltage : 18 W : 6 V 4 A h - 36 W/58 W : 8.4 V 4 A h
- Pre-impregnated fibre glass reinforced polyester body
- Painted sheet steel reflector
- Polycarbonate diffuser
- Elastomer gasket
- Operation : mains power switched on: 2 tubes lit, except 300238
mains power switched off: 1 tube lit (battery back up)
- Battery power supply cut off by a switch which operates when diffuser is opened
- Green LED on when the installation is operating normally and off if there is a mains power failure or a battery fault
- Battery-back up tube identified with green mark
- Battery pack easily interchangeable on site, fixed by screws and equipped with a fast connector
- Ballast and converter fixed by screws
- Closing system using stainless steel clips

Standard version for armoured and non-armoured cable

- One cable entry at each end for M20 cable gland (not supplied)
- Supplied with:
 - Two M20 locknuts and one blanking plug
 - One 2 x (5 x 2.5 mm²) flexible or rigid connection terminal block including 2 earth terminals

Tubes (W) (not supplied)	1 tube standby time	Light output	Weight (Kg)	Volume (dm ³)	Cat. No. 220/240 V	Pack
2 x 18	3 h	29 %	4.5	22.3	300 235	1
2 x 36	3 h	16 %	7	38	300 237	1
2 x 58	3 h	16 %	7.5	45	300 239	1

Fixing accessories

	Cat. No.	Pack
Set of 2 half clamps for fixing to Ø 49 mm (1" 1/2) or Ø 42 mm (1" 1/4) tube For fixing tor Ø 60 mm (2") tube:	 0965 93	1
Set of 2 zinc-plated steel M8 ring bolts for suspending the unit	 0965 94	1
Set of 2 aluminium brackets for fixing unit to flat surface	 0965 97	1
316 stainless steel version	0965 90	1
Set of 2 aluminium hinged brackets for adjusting direction of luminaire when wall-mounted..	 0965 98	1
316 stainless steel version	0965 74	1
Set of 2 zinc-plated steel brackets quick fixing with one hand	 300111	1
316 stainless steel version	 300118	1

For special options, please consult us:

- Tension 110 V
- Ø 38 mm bi-pin tubes
- Ø 38 mm bi-pin tubes specially designed for low temperatures
- Emergency only

Dimensions of fixing accessories (see page 36-37)

Installation method (see page 38-39)

Spare parts (see page 290)

Cable gland :

- polyamide (see page 259)
- metal (see page 258)
- for armoured cable (see pages 252-262)