


254 V bi-pin fluorescent luminaires for armoured or non-armoured cable increased safety



0963 64 Fluo 2 x 36 W



0963 63 Fluo 2 x 18 W

18 and 36 W fluorescent luminaires

- Ø 26 mm bi-pin tubes, standard G 13 lampholders
- Frequency: 50/60 Hz
- Power supply via high frequency electronic ballast 254 V + 6% - 10%, 229 to 269 V
- Instant start. Power factor ≥ 0.95 2 channel ballast
- Pre-impregnated fibre glass reinforced polyester body
- Polycarbonate diffuser hinged to body
- Polycarbonate multi-parabolic hinged reflector
- High temperature internal wiring
- Elastomer gasket
- Anti-vibration lampholders with spring system
- Power supply to the unit cut off by positive safety switch which operates when diffuser is opened, for replacing tubes with mains power switched on
- If one tube fails, the other tube remains lit.
- Open and close using an Allen key or flat screwdriver (system can be disengaged at end of travel)
- IP 2X terminal strip cover for maintaining the ballast and lampholders without cutting off the mains power supply
- Ballast fixed by screws, equipped with a fast connector

Standard twin version for non-armoured cable

- Three threaded cable entries, 2 at one end and the third at the opposite end for M25 cable gland.
- Supplied with:
 - One M25 polyamide cable gland (sealed Ø 8 to 18.5 mm)
 - Two M25 blanking plugs
 - One 5 x 4 mm² max. flexible or 5 x 6 mm² max. rigid connection terminal block

Tube (W) not supplied	Weight (Kg)	Volume (dm ³)	Cat. No. 254V	Pack
2 x 18	5.5	32.3	0963 63	1
2 x 36	7.9	54.2	0963 64	1




Standard twin version for armoured cable

- Two M20 threaded cable entries with earthing plate for armoured cable at one end (cable gland not supplied)
- One clearance hole for M20 cable gland at the opposite end
- Supplied with
 - Two M20 blanking plugs and one M20 locknut
 - One 5 x 4 mm² max. flexible or 5 x 6 mm² max. rigid connection terminal block

Tube (W) not supplied	Weight (Kg)	Volume (dm ³)	Cat. No. 254V	Pack
2 x 18	5.5	32.3	0963 74	1
2 x 36	7.9	54.2	0963 75	1

Part number in bold : fast moving references

Fixing accessories

	Cat. No.	Pack
Set of 2 half clamps for fixing under Ø 49 mm (1" 1/2) or Ø 42 mm (1" 1/4) tube	 0965 93	1
For fixing under Ø 60 mm (2") tube	0965 91	1
Set of 2 zinc-plated steel M8 ring bolts for suspending the unit	 0965 94	1
Set of 2 aluminium brackets for fixing unit to flat surface.	0965 97	1
316 stainless steel version	0965 90	1
Set of 2 aluminium hinged brackets for adjusting direction of luminaire when wall-mounted.	0965 98	1
316 stainless steel version	0965 74	1
Set of 2 zinc-plated brackets for quick fixing with one hand	 0965 96	1
316 stainless steel version	0965 89	1
Fall prevention fixing kit (1.20 m stainless steel chain) for M20 cable entry	0964 06	1
Fall prevention fixing sling (1.20 m stainless steel chain) for M25 cable entry	0964 05	1

For special options, please consult us:

- Single tube
- Fa6 tube
- Pole mounting version
- Special protection of the diffuser against severe chemical attack
- Lens fall prevention fixing kit

Dimensions of fixing accessories (see page 36-37)

Installation and connection method (see page 38-39)

Spare parts (see page 290)

Cable glands for armoured cable (see pages 252-262)